


AE 33 U

Airbandscanner with FM radio





This small and compact handheld scanner receives the complete bandwidth of FM-radio in 50kHz steps.

It is equipped with many advanced functions for professional users.



Features:

▶ 9 pre programmed service bands: 78 - 87,295 MHz: VHF-low (Emergency) 87,3 - 107,95 MHz: FM radio (50 kHz steps) 108 - 137 MHz: Airband (AM) 137 - 174 MHz: 2 m Band (Amateur radio, Freenet, Commercial radio, Marine) 406 - 512 MHz: UHF (Amateur radio, PMR, Commercial radio, Religious radio)

- ▶ 2 selectable country band plans
- ► Frequency steps: 5/6,25/8,33/10/12,5/20 with 15 Offset/50 kHz
- ▶ 180 programmable channels
- ▶ 3 Instant Channels
- ► Memory scan: 30 channels/sec
- ► Scan delay: 2 sec
- ► Memory for channel lockout: 40
- ► Connectors: Antenna (BNC), Stereo earphone (3.5 mm plug)
- ► Battery indicator
- ► Key lock
- ► Illuminated LC-Display
- ► Power supply: 3 x AA alkaline / NiMH batteries
- ► Scope of delivery: Alkaline batteries, Belt clip, Rubber antenna, Stereo earphone

Please note that you may not be allowed to listen to all available frequencies depending on national regulations.

► Ord.-No.: 27034

Fax: +49(0)6103-94 81 60

Alan Electronics GmbH